


DUAL HEAD FLOOD LIGHT INSTRUCTIONS

WARNING: These products may represent a possible shock or fire hazard if improperly installed or attached in any way. Products should be installed in accordance with the owners manual, current electrical codes and/or the current National Electric Code (NEC). Properly ground electrical enclosure. Use only UL or IEC approved wire for input/output connections.

PARTS INCLUDED

- (1) Flood light
- (1) Crossbar
- (2) J-Box mounting screws
- (2) Fixture mounting screws
- (2) Rubber washers
- (2) Canopy mounting nuts
- (3) Wire nuts
- (1) Round plate



CAUTION, IMPORTANT SAFETY INSTRUCTIONS:

- Do not look directly at the operating LED lamp • Do not touch this product with wet hands • Do not disassemble, repair or alter lamp • Suitable for wet locations • The luminaire should be grounded
- To prevent early lamp failure: Lamp should only be installed in operating environments ranging between -20°C and +50°C • This device is not intended for use with emergency exits or emergency lights

To avoid the risk of fire, explosion, or electric shock, this product should be installed, inspected and maintained by a qualified electrician only, in accordance with all applicable electrical codes. Be certain electrical power is OFF before and during installation and maintenance.

Note: Save these instructions for future reference.



For supply connections use wire rated for at least 90°C

CAUTION: Input 120V

LIMITED WARRANTY

This product is warranted to be free from defects in workmanship and materials for up to 5 years from date of purchase. If it fails to do so, please contact Feit Electric at info@feit.com or call 1-866 326-BULB (2852) for instructions on replacement. Do not return the product to the store.

For comments please write to:
 Feit Electric
 Customer Service Department
 4901 Gregg Road, Pico Rivera, CA 90660



This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the

instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures: Reorient or relocate the receiving antenna. Increase the separation between the equipment and receiver. Connect the equipment into an outlet on a circuit different from that to which the receiver is connected. Consult the dealer or an experienced radio/TV technician for help.




WARNING: TURN OFF THE MAIN POWER AT THE CIRCUIT BREAKER BEFORE INSTALLING THE FIXTURE IN ORDER TO PREVENT POSSIBLE ELECTRIC SHOCK.

WARNING: This luminaire should be installed by qualified electrician.

Wall Installation

1. Unscrew the canopy mounting nuts and remove the fixture crossbar (Fig A).


Fig A.



Note: Select your preferred color temperature by using the switch behind the fixture's canopy.


2. Pull the power supply wires to the side and install the fixture crossbar onto the J-box with the screws provided (Fig B).

Fig B.




3. Using the wire nuts provided, connect the bare grounding wires from the fixture to the house ground wires. Connect the white fixture wire to the neutral house wire. Connect the black fixture wire to the power supply wire (Fig C).

Fig C.




4. Adjust the crossbar fixture screws and tighten the center swivel screws. Insert the canopy holes through the fixture mounting screws (Fig D).

Fig D.



5. Position into place and secure the fixture by installing the washers and canopy mounting nuts. Place rubber washers onto fixture, then tighten the nuts (Fig E).

Fig E.




6. Caulk between the light fixture and the wall surface with a silicone sealant (not included).

4 Inch Round External J-Box Installation

1. Unscrew the canopy mounting nuts and remove the fixture crossbar (Fig F).


Fig F.



Note: Select your preferred color temperature by using the switch behind the fixture's canopy.


3. Using the wire nuts provided, connect the bare grounding wires from the fixture to the house ground wires. Connect the white fixture wire to the neutral house wire. Connect the black fixture wire to the power supply wire (Fig H).

Fig H.




2. Before installing the round plate, add silicone sealant between the rear of the round plate J-Box. Pull the power supply wires through the round plate and install the round plate along with the crossbar onto the J-box with the screws provided (Fig G).

Fig G.




4. Adjust the crossbar fixture screws and tighten the center swivel screws. Before installing the fixture canopy, add silicone sealant between the front of the round plate and fixture canopy. Insert the fixture canopy holes through fixture mounting screws (Fig I).

Fig I.



5. Position into place and secure the fixture by installing the washers and canopy mounting nuts. Place the rubber washers onto the fixture then tighten the nuts (Fig J).

Fig J.



COLOR CHANGE SETTINGS

1. You can lock in one color temperature depending on your preference (Fig K).
2. Soft White - Bright White - Daylight
3. When the slide switch is set to SW (Soft White), the color temperature fixes at 3000K.
4. When the slide switch is set to BW (Bright White), the color temperature fixes at 4000K.
5. When the slide switch is set to DL (Daylight), the color temperature fixes at 5000K.



Fig K.

