

# LED LAMP

## SPECIFICATIONS

Enjoy all the benefits of advanced LED energy-saving technology with the Feit Electric BP40G9/830/LEDG2HDRP 40-watt equivalent T4 LED light bulb. This 3000K Bright White dimmable bulb produces 450 lumens using only 4.5 watts of electricity - up to 90% less than an equivalent incandescent light. Get instant on to full brightness with relatively cool running performance. These bulbs have an average life of 10,000 hours / 9.1 years, are RoHS compliant, and are 100% mercury free. Ideal for use in decorative fixtures and chandeliers, choose a dependable Feit Electric specialty light for all your residential or commercial lighting applications

### Ideal For

Signs and Appliances

### Benefits

- Upgrade older specialty lighting to the latest energy saving LED technology
- 3000K Bright White vibrant light ideal for workspaces and task lighting
- Energy efficient LED technology uses considerably less power compared to equivalent incandescent lights
- Long life reduces the inconvenience of replacing bulbs so often
- 10,000 hours / 9.1 years of life (based on 3 hrs of use per day)

### Specifications



| Item Number          | Input Power (Watts)                                      | Incandescent Equiv. (Watts) | Color Temperature    |
|----------------------|--|-----------------------------|----------------------|
| BP40G9/830/LEDG2HDRP | 4.5  | 40                          | 3000 °K (Warm White) |
| Annual Energy Cost   | Life Hours / Years                                       | Energy Efficiency           | Voltage              |
| \$0.54 (Est.)        | 10000 / 9.1  | Up to 88.8%                 | 120                  |
| CRI                  | Shape  | Base                        | Finish               |
| 80                   | T4 (Tubular)   | G9 (Bi-Pin)                 | Clear                |
| Dimmable             | Weights and Measures                                     |                             |                      |
| YES                  | 2.6 in. (Length) / 0.6 in. (Diameter) / 0.1 oz. (Weight) |                             |                      |