



TYPE A T8 LAMPS

Our T8 Linear LED Tube is the most practical cost-effective way to replace a standard fluorescent tube. Plug and play direct replacement makes it easy to install, saves money on repair and maintenance cost and the perfect choice for any application.

Features and Benefits

- Operates off existing ballast
- Compatible with electronic ballasts
- Encased in a film to prevent breakage
- DLC Listed for utility rebates
- 5 Year Warranty
- UL listed
- NSF cert in process



Specifications

Item Number	Input Power (Watts)	Input Line Voltage	Base Type
T4815840/A/LED/MP/12 T4815850/A/LED/MP/12	15	Works off existing ballast voltage	G13
Lumens	Lumen Efficiency (LPW)	CCT	MOL
1920	128	4000K / 5000K	48"
Diameter	Life Hours	Minimum Starting Temperature	Input Current (A)
1"	50,000	-13°F	0.135A