

# SWITCH TO DIM™

Dim with a standard light switch.



1. From the light switch ON position, turn OFF/ON within 2 seconds to cycle through dimming levels.
2. To save a dimming level, leave OFF for at least 5 seconds.

## Features

- No smart home hardware or app required
- Lasts up to 13 years or up to 15,000 hours
- Instant on to full brightness
- Contains no mercury
- Soft White - 2700K



## Specifications

Item#	Replacement	Watts	Lumens	Hours	CRI	Beam Angle	Base	CCT	Volts	MOL	DIA	Pack Method	MANCO
OM60/3DIMCA/LED1	60	10.6	800	15,000	90+	240°	E26	2700K	120	4.4"	2.35"	4/12	17183

# SWITCH TO DIM™

Baissez à l'aide d'un commutateur standard.



1. À partir de la position ON de l'interrupteur de lumière, mettez OFF / ON dans les 2 secondes pour baisser les niveaux de gradation.
2. Pour enregistrer un niveau de gradation, laissez OFF / éteint pendant au moins 5 secondes.



## Caractéristiques

- Aucune application ni aucun matériel informatique requis
- Dure jusqu'à 13 ans ou jusqu'à 15 000 heures
- Instantanée jusqu'à la pleine luminosité
- Sans mercure
- Blanc Doux - 2700K

## Caractéristiques

Article#	Remplacement	Watts	Lumens	Heures	CRI	Angle de faisceau	Base	CCT	Volts	MOL	DIA	Méthode Pack	MANCO
OM60/3DIMCA/LEDI	60	10.6	800	15,000	90+	240°	E26	2700K	120	4.4"	2.35"	4/12	17183